

Dane aktualne na dzień: 03-05-2024 10:15

Link do produktu: <https://www.akumulatory24.pl/yuasa-np3-2-12-p-203.html>

YUASA NP3,2-12 AGM 3,2Ah 12V NP 3,2-12



Cena brutto	99,99 zł
Cena netto	81,29 zł
Dostępność	Dostępny
Czas wysyłki	24 godziny
Numer katalogowy	NP3,2-12
Kod EAN	4016138323658
Producent	Yuasa
Model	NP3,2-12
Napięcie [V]	12
Pojemność [Ah]	3,2
Polaryzacja	Prawy Plus
Długość [mm]	134
Szerokość [mm]	67
Wysokość [mm]	64
Waga [kg]	1,2

Opis produktu

Yuasa Technical Data Sheet

Yuasa NP3.2-12 Industrial VRLA Battery

Specifications

Nominal voltage (V)	12
20-hr rate Capacity to 10.5V at 20°C (Ah)	3.2
10-hr rate Capacity to 10.8V at 20°C (Ah)	2.9

Dimensions

Length (mm)	134 (±1)
Width (mm)	67 (±1)
Height over terminals (mm)	64 (±2)
Mass (kg)	1.2

Terminal Type

FASTON - Quickfit / release (JST where stated)	4.75
--	------

Operating Temperature Range

Storage (in fully charged condition)	-20°C to +60°C
Charge	-15°C to +50°C
Discharge	-20°C to +60°C

Storage

Capacity loss per month at 20°C (% approx.)	3
---	---

Case Material

Standard	ABS (UL94:HB)
----------	---------------

Charge Voltage

Float charge voltage at 20°C (V)/Block	13.65 (±1%)
Float charge voltage at 20°C (V)/Cell	2.275 (±1%)
Float Chg voltage tmp correction factor from std 20°C (mV)	-3
Cyclic (or Boost) charge Voltage at 20°C (V)/Block	14.5 (±3%)
Cyclic (or Boost) charge Voltage at 20°C (V)/Cell	2.42 (±3%)
Cyclic Chg voltage tmp correction factor from std 20°C (mV)	-4

Charge Current

Float charge current limit (A)	No limit
Cyclic (or Boost) charge current limit (A)	0.8

Maximum Discharge Current

1 second (A)	96
1 minute (A)	32

Impedance

Measured at 1 kHz (mΩ)	50
------------------------	----

Design Life & Approvals

EUROBAT Classification: Standard Commercial	3 to 5
Yuasa design life at 20°C (yrs)	up to 5



Layout



3rd Party Certifications

ISO9001 - Quality Management Systems
UNDERWRITERS LABORATORIES Inc.



Safety

Installation

Can be installed and operated in any orientation except permanently inverted.

Handles

Batteries must not be suspended by their handles (where fitted).

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.

Data Sheet generated on 18/03/2016 – E&OE



info@akumulatory24.pl

tel.606 285 285



Zastosowanie:

- Automaty sprzedające
- Aparatura kontrolno-pomiarowa
- Kasy fiskalne
- Komputery
- Narzędzia z napędem elektrycznym
- Parkometry
- Przenośne kamery video
- Systemy alarmowe
- Sprzęt medyczny
- Sprzęt morski i geofizyczny
- Systemy oświetlenia awaryjnego
- Systemy przeciwpożarowe
- Systemy zabezpieczeń
- Systemy zasilania energią słoneczną
- Telewizja kablowa
- Urządzenia biurowe
- Urządzenia automatyki przemysłowej
- Urządzenia gwarantowanego zasilania (UPS)
- Urządzenia telekomunikacyjne
- Zabawki