

Link do produktu: <https://www.akumulatory24.pl/yuasa-np3-6-p-780.html>

YUASA NP3-6 AGM 3Ah 6V NP3-6



Cena brutto	109,00 zł
Cena netto	88,62 zł
Dostępność	Dostępny
Czas wysyłki	24 godziny
Kod producenta	NP3-6
Kod EAN	4016138547443
Producent	Yuasa
Model	NP3-6
Napięcie [V]	6
Pojemność [Ah]	3
Długość [L mm]	134
Szerokość [W mm]	34
Wysokość [H mm]	64

Opis produktu

Yuasa Technical Data Sheet



Yuasa NP3-6 Industrial VRLA Battery

Specifications

Nominal voltage (V) 6

Dimensions

Length (mm) 134 (±1)

Width (mm) 34 (±1)

Height over terminals (mm) 64 (±2)

Mass (kg) 0.66

Terminal Type

FASTON - Quickfit / release (JST where stated) 4.7/6.35

Operating Temperature Range

Storage (in fully charged condition) -20°C to +60°C

Charge -15°C to +50°C

Discharge -20°C to +60°C

Storage

Capacity loss per month at 20°C (% approx.) 3

Case Material

Standard ABS (UL94:HB)

FR version available UL94:V0

Charge Voltage

Float charge voltage at 20°C (V)/Block 6.825 (±1%)

Float charge voltage at 20°C (V)/Cell 2.275 (±1%)

Float Chg voltage tmp correction factor from std -3

20°C (mV)

Cyclic (or Boost) charge Voltage at 20°C (V)/Block 7.26 (±3%)

Cyclic (or Boost) charge Voltage at 20°C (V)/Cell 2.42 (±3%)

Cyclic Chg voltage tmp correction factor from std -4

20°C (mV)

Charge Current

Float charge current limit (A) No limit

Design Life & Approvals

EUROBAT Classification: Standard Commercial 3 to 5 years

Yuasa design life at 20°C (yrs) up to 5



Layout



3rd Party Certifications

ISO9001 - Quality Management Systems



Safety

Installation

Can be installed and operated in orientations up to 90° from the upright position.

Handles

Batteries must not be suspended by their handles (where fitted).

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.



Zastosowanie:

- Systemy UPS
- Systemy nadzoru
- Systemy alarmowe
- Kasy fiskalne
- Zasilanie urządzeń telewizji kablowej
- Sprzęt medyczny
- Zabawki elektryczne
- Motocykle i skutery
- Automatyka przemysłowa